

RS3 PURE SINE WAVE INVERTERS

An Automatic Transfer Switch (ATS) that automatically and seamlessly switches power between battery and mains. An in-built Residual Current Device (RCD) monitors electricity flow, prevents accidents and assists with compliance against local standards.



- Pure sine wave output
- Enhanced surge capacity
- Whisper quiet operation
- Engineered with vibration resistance
- IEC connectors for easy integration
- Optional remote control - **REMOTE-RS**



PRODUCT INFORMATION

Part No.	Input Vdc	Output Vdc	Cont. Output Watts	Surge Watts	Dimensions
R-12-1200RS3	10.5 - 16.5Vdc	240Vac	1200W	2400W	423 x 261 x 126mm
R-24-1200RS3	21.0 - 33.0Vdc	240Vac	1200W	2400W	423 x 261 x 126mm
R-12-2000RS3	10.5 - 16.5Vdc	240Vac	2000W	4000W	443 x 261 x 126mm
R-24-2000RS3	21.0 - 33.0Vdc	240Vac	2000W	4000W	443 x 261 x 126mm
R-12-3000RS3	10.5 - 16.5Vdc	240Vac	3000W	6000W	467 x 318 x 131mm
R-24-3000RS3	21.0 - 33.0Vdc	240Vac	3000W	6000W	467 x 318 x 131mm

REMOTE-RS INVERTER REMOTE WITH 8M LEAD

- Suits REDARC RS series inverters
- Can be flush mounted for professional installations
- Inverter can be installed out-of-sight up to 8m from remote

