

Workshop Series

The HF Series 12/24V Battery Charger & Power Supply is your perfect workshop battery charger. The HF2000 charges and maintains the battery while safeguarding all of the vehicles electronics.

The HF2000 automatic battery charger is controlled by a microprocessor which has a 10 step charging program including a 3 step diagnosis making sure that your battery is perfectly charged every time. The digital display and clearly marked LED indicators ensure that you can always see the status of your battery. A recovery setting can also be used should the battery be deeply discharged

LVHF2000

12/24V 15 Amp Battery Charger



FEATURES:

- 12/24V 15 Amp Battery Charger & Power Supply
- Input Voltage: 240V AC
- Charge Current: 15 A Max @12V / 15 A Max @24V
- Supply Function: 12V & 24V
- Battery Capacity: 30Ah to 500Ah
- Types Of Battery: Wet, Gel, AGM, Mf & VRLA
- Manually Change from the 12 to 24V for charging and supply
- 10 Step Charging Cycle: Analysis 1, Desulphation, Controlled current charge, Ground charge, Constant output charge, Recovery cycle, Analysis 2, Float voltage maintenance, Analysis 3 & Controlled impulse maintenance.
- LED's show the charging cycle along with an LCD display showing battery voltage, amperage & state of charge.
- Protected against: Overheating, short circuits & has a led display warning if the battery is faulty, reverse polarity or voltage is wrong
- Comes with a 6 metre charging cable, complete set of charging accessories, Easy to mount Bracket, Cable Reel & Wall hanger.
- Dimensions: 260 x 135 x 72mm
- Weight: 3.2Kg
- Made In Italy



2 Year Warranty