



## LED HEADLIGHT CONVERSION KITS

- Lumileds Luxeon ZES LED chip
- Reversible aluminium heat sink
- No noisy cooling fan
- Adjustable base for beam and focus adjustment
- Compact size for easy installation
- Operating life: >30000 hours
- Operating temperature: -40°C - +80°C

Kit contents:

- 2 x LED headlight conversion globes
- 2 x external drivers



| PART NO       | BASE | COLOUR TEMP. | BEAM TYPE |
|---------------|------|--------------|-----------|
| <b>LV9300</b> | H1   | 6500K        | Low/High  |
| <b>LV9301</b> | H3   | 6500K        | Low       |
| <b>LV9302</b> | H4   | 6500K        | Low       |
| <b>LV9303</b> | H7   | 6500K        | Low       |
| <b>LV9304</b> | H9   | 6500K        | Low       |
| <b>LV9305</b> | H10  | 6500K        | Low       |
| <b>LV9306</b> | H11  | 6500K        | Low       |
| <b>LV9307</b> | HB3  | 6500K        | Low       |
| <b>LV9308</b> | HB4  | 6500K        | Low       |
| <b>LV9309</b> | HB5  | 6500K        | Low/High  |
| <b>LV9310</b> | HIR2 | 6500K        | Low       |
| <b>LV9311</b> | H15  | 6500K        | Low       |

## COMPANION ITEMS

### PLUG & PLAY



| ELECTRONIC CAN BUS CANCELLERS |         |         |      |
|-------------------------------|---------|---------|------|
| PART NO                       | VOLTAGE | BASE    | PACK |
| <b>LV9320</b>                 | 12V     | H4      | 2    |
| <b>LV9321</b>                 | 12V     | H7      | 2    |
| <b>LV9324</b>                 | 12V     | H8/H11  | 2    |
| <b>LV9326</b>                 | 12V     | HB3/HB4 | 2    |

| RESISTOR CAN BUS CANCELLERS |         |      |      |
|-----------------------------|---------|------|------|
| PART NO                     | VOLTAGE | BASE | PACK |
| <b>LV9322</b>               | 12V     | H4   | 2    |
| <b>LV9323</b>               | 12V     | H7   | 2    |
| <b>LV9325</b>               | 12V     | H11  | 2    |